



DIP5	DIP6	MAXIMUM CURRENT
ON	ON	15A
OFF	ON	20A
ON	OFF	25A
OFF	OFF	30A

DIP7	DIP8	NOMINAL BATTERY VOLTAGE	
		lead-acid	LiFePO4
ON	ON	12V	12.8V
OFF	ON	24V	25.6V
ON	OFF	36V	38.4V
OFF	OFF	48V	51.2V

**IMPORTANT:**

This document should not be used to change charger settings unless you have experience and knowledge of battery types and battery charging or unless you have been trained by and/or supervised by a suitably knowledgeable and experienced person.

Incorrect settings can lead to shortened battery life, battery damage or safety issues.

Always verify the settings by restarting the charger before putting the charger into service.

Read the Operating Manual.

Firmware:  
010-103-008

June 16, 2026

Ph: 905.636.9865

E-Mail [info@bti-chargers.com](mailto:info@bti-chargers.com) Web: [www.bti-chargers.com](http://www.bti-chargers.com)